Troubleshooting Guide LightSync 0-10V Dimmer Module

LSDM Part# 97013537

The dimmable lights do not dim

- Verify proper 0-10V dimming control voltage from fixtures: 9-15vdc when disconnected from the Dimming Module. Lights should be at full brightness when wires are separated and dimmed to the lowest level when shorted together. If the lights do not change level, then you may have an open connection.
- Failure to dim is often caused by a reversal of polarity somewhere in a run of multiple ballasts/drivers.
- Verify all terminations in problem circuit.

The dimming does not ramp down past a certain point, or the lights are dim all the time.

- Check polarity on the dimming outputs. Polarity is important: Purple +, Gray/Purple –
- Failure to dim completely is usually caused by a bad dimming ballast/driver. Due to the ballasts and
 drivers being parallel if one ballast or driver is bad and is at a low voltage output it will be at a low
 level. To troubleshoot, remove all except the first in line and keep adding one at a time back online
 until you determine which one brings down the run.

Communication Issues

- Does the Panel see the Module as "Connected"?
- Is the Module addressed correctly? (Remember 0s down for proper reference)
- Panel Mount- Is the 6-pin connector correctly aligned and firmly seated to output board?
- <u>Remote Mount</u>- Are Data Cables connected to correct In/Out ports and seated properly? IN port does not pass power to other downstream devices.
 - Test Data Cables for damage and verify data cables are terminated properly (T568B standard) using a cable tester.



Troubleshooting Guide LightSync 0-10V Dimmer Module

LSDM Part# 97013537



